

IN THE CLAIMS:

1. (Original) A variable reluctance resolver having a rotor which comprises a noncircular core and which is rotatably supported inside a stator with a gap therebetween, the shape of the rotor being such that the gap permeance, which is based on the gap, varies according to a sine function of the rotational angle, wherein each salient pole of the rotor has a center which is offset by a prescribed offset distance in the radial direction from the center of the rotor, and the outer peripheral shape of each salient pole comprises by an arc of a circle of radius r which is centered on the center of the salient pole and which does not extend to the inner peripheral surface of the stator.

2. (Original) A variable reluctance resolver as claimed in claim 1 wherein the shape of the rotor is defined in accordance with the rotational angle, which is expressed by the mechanical angle ϕ or the electrical angle θ corrected by the shaft angle multiplier, and the offset distance A such that the outer radius R_r of the rotor has a value given by the following equation:

$$R_r = A \cos \phi + \sqrt{r^2 - A^2 \sin^2 \phi} = A \cos(\theta/N) + \sqrt{r^2 - A^2 \sin^2(\theta/N)}$$

wherein r is the radius of each salient pole, A is the offset distance, ϕ is the mechanical angle (ϕ = electrical angle θ /shaft angle multiplier N), θ is the electrical angle, and N is the shaft angle multiplier.

3. (Currently Amended) A variable reluctance resolver as claimed in claim 1 or claim 2 wherein the shape of the rotor is defined in accordance with the rotational angle, which is expressed by the mechanical angle ϕ or the electrical angle θ corrected by the shaft angle multiplier, such that the gap δ between the stator and the rotor has a value given by the following equation:

$$\delta = R_s - A \cos \phi - \sqrt{r^2 - A^2 \sin^2 \phi} = R_s - A \cos(\theta/N) - \sqrt{r^2 - A^2 \sin^2(\theta/N)}$$

wherein δ is the gap, R_s is the inner radius of the stator, A is the offset distance, ϕ is the mechanical angle ($\phi = \text{electrical angle } \theta / \text{shaft angle multiplier } N$), θ is the electrical angle, N is the shaft angle multiplier, and r is the radius of each salient pole.